

**IN THE CLAIMS**

1. (previously presented) A method of displaying an input signal, the method comprising:
  - sampling the input signal;
  - searching for a zero space pattern in the sampled signal;
  - locating a first zero space;
  - locating a second zero space, following the first zero space;
  - calculating bit period of the input signal by determining time period between the first zero space and the second zero space; and
  - displaying the input signal using the calculated bit period as the basis for a scale.
2. (original) The method recited in claim 1 further comprising initializing offset and time scale.
3. (original) The method recited in claim 1 further comprising determining whether NRZ autoscale is applicable.
4. (original) The method recited in claim 1 wherein the step of locating the first zero space comprises:
  - locating a first transition,  $X_1$ , where value of the input signal is more than a threshold value,  $V_{THRES}$ , before the first transition,  $X_1$ , but less than the threshold value,  $V_{THRES}$ , after the first transition,  $X_1$ , the first transition,  $X_1$ , being the first such transition following the offset; and
  - locating a second transition,  $X_2$ , where value of the input signal is less than the threshold value,  $V_{THRES}$ , before the second transition,  $X_2$ , but more than the threshold value,  $V_{THRES}$ , after the second transition,  $X_2$ , the second transition,  $X_2$ , being the first such transition following the first transition,  $X_1$ .

5. (original) The method recited in claim 4 wherein the step of locating the second zero space comprises:

locating a third transition,  $X_3$ , where value of the input signal is more than a threshold value,  $V_{THRES}$ , before the third transition,  $X_3$ , but less than the threshold value,  $V_{THRES}$ , after the third transition,  $X_3$ , the third transition,  $X_3$ , being the first such transition following the second transition,  $X_2$ ; and

locating a fourth transition,  $X_4$ , where value of the input signal is less than the threshold value,  $V_{THRES}$ , before the fourth transition,  $X_4$ , but more than the threshold value,  $V_{THRES}$ , after the fourth transition,  $X_4$ , the fourth transition,  $X_4$ , being the first such transition following the third transition,  $X_3$ .

6. (original) The method recited in claim 5 wherein the step of calculating the bit period comprises determining temporal difference between the third transition,  $X_3$ , and the first transition,  $X_1$ .

7. (original) The method recited in claim 1 further comprising displaying the input signal using a multiple of the calculated bit period as the scale.

8. (previously presented) An apparatus for displaying an input signal, the apparatus comprising:

a processor;

storage connected to the processor, the storage including instructions for the processor to

sample the input signal;

search for a zero space pattern in the sampled signal;

locate a first zero space;

locate a second zero space, following the first zero space;

calculate bit period of the input signal by determining time period between the first zero space and the second zero space; and

display the input signal using the calculated bit period as the basis for a scale.

9. (original) The apparatus recited in claim 8 wherein the storage further comprises instructions for the processor to initialize offset and time scale.
10. (original) The apparatus recited in claim 8 wherein the storage further comprises instructions for the processor to determine whether NRZ autoscale is applicable.
11. (original) The apparatus recited in claim 8 wherein the storage further comprises instructions for the processor to:
- locate a first transition,  $X_1$ , where value of the input signal is more than a threshold value,  $V_{THRES}$ , before the first transition,  $X_1$ , but less than the threshold value,  $V_{THRES}$ , after the first transition,  $X_1$ , the first transition,  $X_1$ , being the first such transition following the offset; and
  - locate a second transition,  $X_2$ , where value of the input signal is less than the threshold value,  $V_{THRES}$ , before the second transition,  $X_2$ , but more than the threshold value,  $V_{THRES}$ , after the second transition,  $X_2$ , the second transition,  $X_2$ , being the first such transition following the first transition,  $X_1$ .
12. (original) The apparatus recited in claim 11 wherein the storage further comprises instructions for the processor to:
- locate a third transition,  $X_3$ , where value of the input signal is more than a threshold value,  $V_{THRES}$ , before the third transition,  $X_3$ , but less than the threshold value,  $V_{THRES}$ , after the third transition,  $X_3$ , the third transition,  $X_3$ , being the first such transition following the second transition,  $X_2$ ; and
  - locate a fourth transition,  $X_4$ , where value of the input signal is less than the threshold value,  $V_{THRES}$ , before the fourth transition,  $X_4$ , but more than the threshold value,  $V_{THRES}$ , after the fourth transition,  $X_4$ , the fourth transition,  $X_4$ , being the first such transition following the third transition,  $X_3$ .
13. (previously presented) The apparatus recited in claim 5 8 wherein the storage further comprises instructions for the processor to determine temporal difference

between the third transition,  $X_3$ , and the first transition,  $X_1$ .

14. (original) The apparatus recited in claim 13 wherein the storage further comprises instructions for the processor to display the input signal using a multiple of the calculated bit period as the scale.
15. (previously presented) A machine readable medium comprising program for the machine to display an input signal, the program comprising instructions for the machine to:
- sample the input signal;
  - search for a zero space pattern in the sampled signal;
  - locate a first zero space;
  - locate a second zero space, following the first zero space;
  - calculate bit period of the input signal by determining time period between the first zero space and the second zero space; and
  - display the input signal using the calculated bit period as the basis for a scale.
16. (original) The medium recited in claim 15 wherein the medium is selected from a group consisting of magnetic disc, optical disc, read only memory (ROM), random access memory (RAM), harddrive, compact disc (CD), flash memory, and solid state memory.

//

//

//